# ML-H803TC



#### 1. Features

(1). ML-H803TC can work with PC(online), SD card(offline) or DMX console.

(2). ML-H803TC drives maximum 170000 pixels, 2 ports control maximum 255 slave controllers.

(3). Slave controller is H802RA or ML-H801RC.

(4). By combining ML-H803TC with H802RA, you can set address for DMX512 chips.

(5). ML-H803TC transmits signal based on Ethernet Protocol. Max transmission distance from ML-H803TC to slave controller is 100 meters.

(6). Use four buttons to switch files, set play mode, speed and brightness.

(7). SD card supports FAT32, FAT16 format, maximum capacity is 64G bytes, stores up to 64 DAT files.

(8).Support Encryption of power-up times.

#### 2. Supported Driver Chips

LPD6803, LPD8806, LPD6812, LPD6813, LPD1882, LPD1889, LPD1883, LPD1886, DMX512, HDMX, APA102, P9813, LD1510, LD1512, LD1530, LD1532, UCS6909, UCS6912, UCS1903, UCS1909, UCS1912, WS2801, WS2803, WS2811, WS2812, DZ2809, SM16716, TLS3001, TLS3002, TM1812, TM1809, TM1804, TM1803, TM1914, TM1926, TM1829, TM1906, INK1003, BS0825, BS0815, BS0901, LY6620, DM412, DM413, DM114, DM115, DM13C, DM134, DM135, DM136, 74HC595, 6B595, MBI6023, MBI6024, MBI5001, MBI5168, MBI5016, MBI5026, MBI5027, TB62726, TB62706, ST2221A, ST2221C, XLT5026, ZQL9712, ZQL9712HV, etc.

Note: ML-H803TC supports more than the chips listed above(some chips have the same sequence diagram, for example: UCS512, WS2821 and DMX512 have the same protocol, ML-H803TC supports them all).

#### 3. Basic Workflow

Work with SD card(offline)

Step1. Connect lights, slave controller and ML-H803TC like the following image.(I didn't draw power supply)

you can only use NET1.



For example:

if you want to control WS2812B strip, just connect GND, DI on strip to GND, DAT on slave controller.



## Step2. Download and Install LED Build Software

In this mode, you will need LED Build Software.

LED Build Software

Download: https://drive.google.com/open?id=0B1gzqyV6hfOgUDZ

BVI84SmRDV28

LED Build Software Tutorial Video:

https://drive.google.com/open?id=0B1gzqyV6hfOgUnFjeG9EM3VR

ZjA

Step3. Program in LED Build Software

Basic software workflow

#### **1. Place Pixels**

For example there are 1 slave controller(ML-H801RC) connected

#### to ML-H803TC



2. Light Setting



#### 3. Make Effects



# 4. Output controller data and put it into SD card



For more details of software operation, please refer to the video

post above.

Step4. Configure ML-H803TC with 4 buttons

Power ML-H803TC on

Long press "MENU" button to switch to English



#### Switch files



Set Playback Mode, press "OK" to save



Set speed, press "OK" to save



### Set brightness



Set DMX Address for ML-H803TC

This function is used when ML-H803TC is connected to DMX

console



For example:

If DMX Address is 1, you can use channel 1,2,3 on DMX Console to switch files, change speed and brightness.

If DMX Address is 3, you can use channel 3,4,5 on DMX Console to switch files, change speed and brightness.

In a word, the DMX Address is the starting channel on DMX Console.

Press "OK" to start addressing.



Work with PC(online)

Step1. Connect lights, slave controllers and ML-H803TC like the following image.



# Step2. Download and Install LED Studio Software

In this mode, you will need LED Studio Software.

LED Studio download link:

https://drive.google.com/open?id=0B1gzqyV6hfOgWFpuM3BoN1V

aTGs

# Step3. NET2 Setting

In online mode, NET2 transmits data received from PC to NET1.



Network Port 2 connects the computer through the network cable, and Network Port 1 connects the decentralized control. Network Port 1 forwards the data received by Network Port 2, which can realize the computer control.

## Step4. Allocate an IP address for ML-H803TC

Control Panel Home	View your basic network infor	mation and set up connections				
	View your active networks					
Change adapter settings						
Change advance sharing	未识别的网络	Access type: No network access				
ettings	Public network	Connections: 掌本地连接				
1	Change your networking settings					
	Set up a new connection or n	network				
	Set up a broadband, dial-up, or VPN connection; or set up a router or access point.					
	Troubleshoot problems					
	Troubleshoot problems					
	Troubleshoot problems Diagnose and repair network	problems, or get troubleshooting information.				
Control Panel\Network ar	Troubleshoot problems Diagnose and repair network	problems, or get troubleshooting information.				
😰 Control Panel\Network ar	Troubleshoot problems Diagnose and repair network nd Internet\Network Connections ontrol Panel > Network and Internet > Network and Inter	problems, or get troubleshooting information. etwork Connections				
Control Panel\Network ar To the second se	Troubleshoot problems Diagnose and repair network nd Internet\Network Connections ontrol Panel > Network and Internet > Net Advanced Help	problems, or get troubleshooting information. etwork Connections				
Control Panel\Network ar ← → ↑ ♀ > Control Panel\Network ar File Edit View Tools Organize ▼	Troubleshoot problems Diagnose and repair network nd Internet\Network Connections ontrol Panel > Network and Internet > Ne Advanced Help	problems, or get troubleshooting information. etwork Connections				



Connect using:	ADDIEL DOLE COM	shit Bhamat Conter
This connection uses	the following tems:	Coofigure
● GoS 数据包 ● Internet 协议 ● 結路层拓扑 ● Microsoft 网 ● Microsoft LL ● ● 链路层拓扑	计划程序 (版本 6 (TCP/IPv6) 发现映射器 I/O 驱动 给适配器多路传道: 15 <del>次本 4 (TCP/IPv4)</del> DP 协议驱动程序 发现响应程序	程序 协议 2
<	1.6	*
Install	Uninstall	Properties
Description 传输控制协议/Int 协议,用于在不同	ernet 协议。该协议是 附为相互连接的网络上	默认的广域网络 上通信。

General			
You can get IP settings assigned this capability. Otherwise, you n for the appropriate IP settings.	automatically if your eed to ask your netwo	network suppo ork administrat	orts tor
Obtain an IP address auton	natically	-	/
Use the following IP addres	s:	-	-
IP address:	192 . 168 .	6.5	
Subnet mask:	255 . 255 . 2	255 . 0	
Default gateway:	1		
Obtain DNS server address	automatically		
Use the following DNS server	er addresses:		
Preferred DNS server:			
Alternate DNS server:			
1522			

## Step5. Program in LED Studio Software

#### Basic software workflow

#### 1. Place Pixels

For example there are 4 slave controllers(ML-H801RC) connected

to ML-H803TC, 8 ports of ML-H801RC are all connected to leds.

In LED Studio



## 2. Slave Setting

0 📽 🖬	<b>n</b> a	¥ 6	Ø @ X ♡ ↔	88 🛛 🛛 🖊												
Connection	mode			0-0-0				000	-0-0-0	0-0-0						
<ul> <li>Single I</li> </ul>	Row												•••			
⊖ Single (	Col															
OReturn	Row			Slave settin	g									×		
OReturn	Col			Deconstruction of the local de				-			-		process		-	
O Shor di	stance			Bright 1	00 💌	Red:	100		Green:	100	-	Blu	ie: 100			
O Short d	ist row		-	ClockRate	e: 1.00 ~	MHz Port N	lumber:	8 ~	Gamr	na: 2.2			ColorR	everse	2	
ight line wi	th a slave	~		LightType	RGB	~ Add	Color	Test		IC Type	TM18	312	v		•	
dule: Sir	ngle pixel	~		No.	LightType	IC Type	Clock	Bright	Reverse	Ports	Red	Gre	Blue	Ga		
al imitDiva	32			1	RGB	TM1812	1.00	100	No	8	100	100	100	2.2		
echnike ike	13. 15.	-		2 7	RGB	TM1812	1.00	100	No	8	100	100	100	2.2	-	
i. 1	Count	^		3	RGB	TM1812	1.00	100	No	8	100	100	100	2.2		
1	32			4	RGB	TM1812	1.00	100	No	8	100	100	100	2.2		
2	32				1											
3	32			S	ave n	umber									-•	
1	32															
	32															
5	32	- 11		Each	claure	control	lor	an b		fin	rod	line	livid	hually		
7	32	- 1		EdCII	Slave	contro	lier o	an L	e coi	mgu	irea	inc	IVIO	iualiy	•	
8	32			whic	h mea	ns the	light	t typ	e, IC 1	type	, etc	CO	uld I	be		
3	32	- 1		diffe	rent.											
10	32	- 1					_				_	_	_	_		
11	32								1	OK	1	Inneal		innly		
12	32	- 1								UN.		/drivel		4Phil	•	
13	32	~		-				-		-	-				- •	
		-														
es number	32															
			10-1		000		0.0	000	001	9 0 0		0.0				
							0.0		0.01	5 0 0	-0-8	8 8	100	8 8 8		

onnect Singl	ion mode e Row						••••		•••			•••			•••	
ve sett	ing						****		×	144						
riabt [	100	Red	100	-	Green:	100 🔽	Blue	10		••		•••			••	
	1.00	ULL: Dod b	humber	8	Came	22		alor								
IUCKPCa		MITE FUILT	umper.		Garm	10.7		OIUIN	leveise							
ghtTyp	e: RGB	✓ Add	Color	rest		IC Type:	HasEnable	~		-0-0-	0-0-0	0-0-0				
No.	LightType	IC Type	Clock	Bright	Reverse	Ports	LPD1883	-	Ga		0-0-0	000				
1	RGB	TM1812	1.00	100	No	8	LPD6803		2.2			0-0-0				
2	RGB	TM1812	1.00	100	No	8	LPD1886		22							
3	RGB	TM1812	1.00	100	No	8	LPD1882	-	22	0.0-1	6-6-6		0.01	0.0.0	-0-0	
1	RGB	TM1812	1.00	100	No	8	TM1812	P	9883,TM	804,TM180	9,UCS19	03,UCS1	09,UCS19	12,WS2811	WS2812,	SM16703
							TM1803 DMX512			0.0	9-0-0		0-0-0-1		-0-0	
							HDMX									
							WS2803								-0-0	
							WS2801									
							TM1829									
							APA102					0.04				
							APA102-65536									
							TLS3001				8-0-0	-0-0-0				
							DM413									
							DM412									
					-		MY9221									
						OK	MY9231	- 3	pply							
							SM16716									
13	32	~					BS0825				0-0-0				•••	
	20	_					BS0901									
s numb	ier: 32						BS0815		0-0						0.0	
				100	8 6 6 1	0 0 0	LD15xx		100.00.	B B B I	8 8 8	0.0.4	0 0 1	5 6 6 6	0.0	

# Note: many chips share one option, for example:

# 3. Multi-Net Setting

IP	SlaveNO.	SlaveN	
192.168.6.255	1 - 4	4	
192.168.1.255		0	
Local IP			

# 4. Make Effects



#### 4. Control DMX512 chip lights

ML-H803TC can control ML-H801RC, H802RA two kinds of slave controllers(they all support DMX512 protocol),

but by using ML-H803TC + H802RA, you can set DMX address for DMX512 chips.



Take TM512 strip for example:

Step1. Set them up



Step2. Set address with four buttons

In this mode press OK



#### Choose chip:



#### Set channel number of each chip occupies



#### Set starting address

LCD DISPLAY			
Address:1 SET->SetAddress	menu 🥥	~	🍥 ок

#### Addressing

POWER	LCD DISPLAY	
10	Address:1 Addressing	MENU 🌍

### 5. 803TC Cloud Control or LAN Control

#### ML-H803TC LAN Control



When multiple 803TC ports 2 are connected to the same router to achieve multiple 803TC synchronization, the first 803TC is set to send synchronization of ports 2 to achieve multiple 803TC synchronization.

# LCD DISPLAY Met2CloudCtr1: D:259

#### ML-H803TC Cloud Control

When this mode is set up, the network port 2 connects the router which can be connected to the network, and the network port 1 connects the sub-control. The remote cloud control can be carried out through software LED CLOUD or mobile phone APP. Each 803TC has its own ID code, which requires binding devices when using cloud control.

登陆		×
注册新用)	<b>à</b>	取消
用户名:		确定
密码:		

803TC cloud control. When 803TC's gateway 2 is connected to a networked router, open the LED CLOUD software, and no account can be registered.

ID	备注名					
		☆ 1				
		速 25				
		亮 16				_
			执行			
			_			
		设置同步		取	消同步	
		控制器授权		控制器	器解除授	权
						100051

The login interface is shown in the following figure. Click on the controller binding and enter the ID number of 803TC you are using. Note: The ID of each 803TC is different. If other users want to use LED CLOUD to control 803TC after binding, they need to authorize the first binding user.

ID	备注名	

After binding the controller, the device you bind will appear on the left. If you bind more than one controller, it will display more than one controller ID. You can switch files, brightness and speed by clicking.

#### 6.

Input Voltage: Customized

Power Consumption: 1W

Drive Pixels Number: 170000

Weight: 1.1KG